



# Cascade Flex E

## *Part Code Logic*

July 2024

# Part Code Logic – Cascade Flex E



Range Prefix	Driver	Integrated Controls	Size, Optic, Notional Output	Light Source Colour	Ceiling Type	Emergency
CE = Cascade Flex E	H = Fixed Output  Y = DALI	Blank = None  RG = Organic Response	1 = 600x600, Pod, 2300lumen 2 = 600x600, Pod, 3300lumen 3 = 600x600, Pod, 4100 lumen 4 = 600x600, Pod, 4800lumen 5 = 600x600, Diff, 2300lumen 6 = 600x600, Diff, 3300lumen 7 = 600x600, Diff, 4100 lumen 8 = 600x600, Diff, 5100lumen 9 = 1200x300, Pod, 3300lumen 10 = 1200x300, Pod, 4100 lumen 11 = 1200x300, Pod, 4800lumen	3K8 = 3000K Ra80 3K9 = 3000K Ra90 4K8 = 4000K Ra80 4K9 = 4000K Ra90	XT = Exposed T ST = Spring T Blank = SAS 330	Blank = None  EM = 3hr  EP = COMEPS  EW = Routefinder Wireless

- Routefinder Wireless and Organic Response combined not available
- XT & ST Only available for 600x600 luminaires
- SAS 330 only available for 1200x300 luminaires.
- Notional output as 4K Ra80